

This document details how to configure your Macintosh computer running on OS X to dial OpenAccess. If you are using an earlier Macintosh operating system, please refer to the "Macintosh Dial-Up Settings" help sheet.

1. Open the "System Preferences" Panel (see Figure 1).

- Click on the apple to open the "Apple Menu" in the top left-hand corner of the desktop.
- Select "System Preferences."



Fig. 1 – Getting to the "System Preferences" Configuration Screen.

2. Click on the "Network" icon at the top of the window (see Figure 2).

| 00 | | Network | | |
|---|-------------------------|--|--------------------|--|
| Show All Dis | splays Sound | Network | Startup Disk | |
| | Location: (| Automatic | • | |
| Configure: In | ternal Modem | * | ~ | |
| | TCP/IP | PPP Proxie | s Modem | - |
| Service Provider: Telephone Number: 647-0808 | | | | (Optional) |
| Alternate Number: | | | | (Optional) |
| | Account Name: use | ername | |] |
| Password: | | | |] |
| | | Save password checking this bas access this Intern PP Options | et account without | f this computer to entering a password. |
| Click the l | lock to prevent further | changes. | | Save |

Fig. 2 - The Network configuration panel

- 3. Click on the "PPP" tab and enter your information in the text boxes (see Figure 2).
 - In the "Telephone Number:" text box type "647-0808."
 - Enter the User Name given to you by OpenAccess in the "Account Name" text box.
 - Enter the password given to you by OpenAccess in the "Password" text box.
 - Click on SAVE when you've entered all of the information.
 - Close the Network Window.
- 4. Click on the "Go" menu at the top of the desktop and select "Applications."

5. Double-click on the "Internet Connections" icon.

• This will bring up the "Internal Modem" window (see Figure 3).

| g. 3 – The Internal Moder | n Window. Internal Modem | |
|---------------------------|-----------------------------|-------------|
| Configuration: | Internal Modem | |
| Service Provider: | Charter | |
| Telephone Number: | 647-0908 | |
| Alternate Number: | | |
| Name: | username | |
| Password: | ••••• | |
| These settings can be | changed in Network Prefere | ences. Edit |
| Status: | Idle | Connect |
| | | |

6. Click on the CONNECT button.